



26V BATTERY



For Cinema Cameras and High Power LED Lights

Fxlion designed the first 26V V-Mount battery for today's high power LED lights and professional cinema cameras. Reliable build quality and safety features to protect from over-heating, over-current, over-charge, and over-discharge are built in to every Fxlion battery. With a normal working current of 10 Amps at 26VDC the battery will provide the working power you need to get through your next project. If your equipment uses more than the 10 Amps – you can get a maximum of 15 Amps Output.



APPLICATIONS:

ARRI LF Camera and 24V LED Lights such as the Zylight F8-200 Fresnel. To power your lights with 26V batteries, choose from either the Fxlion SKY TWO (24V/48V) or SKY THREE (48V) power solutions.

FEATURES AND ADVANTAGES:

- High Power. High Current up to 15A (Working Current 10A)
- High Efficiency, Low Heat, Good for 24V – 30V Cameras and LED Lights.
- Working Temp: -20°C to 55°C; -4°F to 131°F
- 4-Level LED Power Indicator
- D-Tap IN/OUT Output 26V
- PCB Design: Over-Heat, Over-Charge, Over-Discharge, and Over-Current Protection



SPECIFICATIONS & ACCESSORIES

LED Indicator
4-Level Capacity Indication



Plugs
1 x D-Tap Input / Output (Only 26V)

230Wh 26V BATTERY

Mounting	Part Number	Item Number
V-Mount	BP-7S230	1004406
Gold-Mount	AN-7S230	1005011
Capacity	9.0Ah, 230Wh	
Voltage	26V	
D-Tap Input / Output	Yes (1X) 26V	
Load	15.0A (Max.)	
Dimensions	152(L)mm × 97(W)mm × 65(H)mm	
Weight	1180g	



270Wh 26V BATTERY

Mounting	Part Number	Item Number
V-Mount	BP-7S270	1004989
Gold-Mount	AN-7S270	1005062
Capacity	10.5Ah, 270Wh	
Voltage	26V	
D-Tap Input / Output	Yes (1X) 26V	
Load	15.0A (Max.)	
Dimensions	152(L)mm × 97(W)mm × 65(H)mm	
Weight	1190g	

ACCESSORIES

Part Number	Item Number	Description	
PL-7110-B01	1004573	26V D-Tap Standard Charger	Specialized D-Tap Cable charger only for 26V Lithium-ion batteries. Input: 100-240V AC 47-63Hz Charging Output: 29.4V/2.0A
PL-7S2DA	1005061	26V Dual Channel Deck Charger - Gold-Mount	Specialized Dual Channel Deck charger only for 26V Lithium-ion batteries. Input: 100-240V AC 47-63Hz Two channels synchronous charging. Charging Output: 29.4V/2.0A x 2
PL-7S2DS	1004414	26V Dual Channel Deck Charger - V-Mount	Specialized Dual Channel Deck charger only for 26V Lithium-ion batteries. Input: 100-240V AC 47-63Hz Two channels synchronous charging. Charging Output: 29.4V/2.0A x 2
FX-4S7S2A	1005196	Bi-Volt Battery Charger - V-Mount	Automatic Voltage Detection for 14.4V or 26V batteries. 2 Channel Simultaneous Charging. Compact in Size and Ideal for Travel. Charging Indicator for Each Battery Channel
FX-4S7S2D	1005266	Bi-Volt Battery Charger - Gold-Mount	Automatic Voltage Detection for 14.4V or 26V batteries. 2 Channel Simultaneous Charging. Compact in Size and Ideal for Travel. Charging Indicator for Each Battery Channel

⚠ CALIFORNIA PROPOSITION 65 WARNING: Lithium-ion Batteries and/or products that contain Lithium-ion Batteries can expose you to chemicals including cobalt lithium nickel oxide, and nickel, which are known to the State of California to cause cancer and birth defects or other reproductive harm. For more information, go to www.P65Warnings.ca.gov.